

Backup Box-PLUS



- On/Off-Grid Switching
- Grid Monitoring
- Built-In Grid Meter & PV Meter



Specifications	
Phase	Three Phase
Max. Input / Output Current	63 A / 63 A / 63 A
Grid Voltage Range	184 ~ 264.5 V (L-N)
Grid Frequency	50 / 60 Hz
Display	LCD
Communication	RS-485
Operating Temperature	-10 °C ~ 50 °C
Relative Humidity	15% ~ 85%
IP Protection	IP21
Dimensions (W x D x H)	410 x 169.2 x 605 mm
Net Weight	17.6 kg
Compatible Energy Storage Systems	SMILE5 / SMILE-T10 / SMILE-S6-HV SMILE-T10-HV / SMILE-G3-S3.6/S5/B5 SMILE-G3-T4/T5/T6/T8/T10 / SMILE-G3-T12/T15/T20
Warranty	5 Years



Alpha ESS Co., Ltd.
☎ +86 513 8060 6891
✉ info@alpha-ess.com
🌐 www.alphaess.com
📍 No. 1086, Bihua Road, Nantong Hi-Tech Zone, Jiangsu Province, China

Alpha ESS Europe GmbH
☎ +49 610 3459 1601
✉ europe@alpha-ess.de
🌐 www.alphaess.de
📍 Paul-Ehrlich-Straße 1a, Langen, Hessen D-63225 Germany

Alpha ESS Australia Pty. Ltd.
☎ +61 02 9000 7676
✉ techsupport@alphaess.au
🌐 www.alphaess.com
📍 8/15-21 Gibbs Street, Chatswood, NSW 2067 Australia

Alpha ESS International Pte. Ltd.
☎ +65 6513 1125 / +65 6513 1126
✉ Singapore@alpha-ess.com
🌐 2 Corporation Road #01-06A Corporation Place 618494 Singapore

Alpha ESS Italy S.r.l.
☎ +39 339 462 4288
✉ info@alpha-ess.it
🌐 www.alphaess.com
📍 Via Don Minzoni, 17, Calenzano Firenze 50041 Italy

Alpha ESS UK Ltd.
☎ +44 0330 043 2610
✉ info@alpha-ess.com
📍 Drake house, Long street, Dursley, GL11 4HH UK

Alpha ESS USA, Inc.
☎ +1 408 368 7828
✉ usa@alpha-ess.com
📍 Unit 5 2180 S Ivanhoe St, Denver, CO 80222 USA

Alpha ESS Korea Co., Ltd.
✉ info@alpha-ess.com
📍 2F, 19-4, Nohyeong 11-gil, Jeju-si, Jeju-do, Republic of Korea

Alpha ESS South Africa (Pty.) Ltd.
✉ measervice@alpha-ess.com
📍 La Rocca Office Park, Block B1 321 Main Road, Bryanston, Johannesburg, 2191